

DESIGN KIT

WE-CBF Large Size



1206	742 792 1 ■	742 792 11 ■	742 792 122 ■	742 792 13 ■	742 792 133 ■	742 792 14 ■
	Z@100 MHz: 32 Ω DCR: 0.20 Ω I _H : 500 mA Z*: 70 Ω @ 1000 MHz	Z@100 MHz: 90 Ω DCR: 0.30 Ω I _H : 300 mA Z*: 170 Ω @ 550 MHz	Z@100 MHz: 220 Ω DCR: 0.30 Ω I _H : 300 mA Z*: 240 Ω @ 200 MHz	Z@100 MHz: 600 Ω DCR: 0.30 Ω I _H : 200 mA Z*: 600 Ω @ 100 MHz	Z@100 MHz: 600 Ω DCR: 0.30 Ω I _H : 500 mA Z*: 750 Ω @ 60 MHz	Z@100 MHz: 1000 Ω DCR: 0.45 Ω I _H : 200 mA Z*: 1250 Ω @ 75 MHz
1210	742 792 112 ■	742 792 15 ■	742 792 121 ■	742 792 18 ■	742 792 141 ■	
	Z@100 MHz: 31 Ω DCR: 0.04 Ω I _H : 3000 mA Z*: 52 Ω @ 1000 MHz	Z@100 MHz: 80 Ω DCR: 0.03 Ω I _H : 3000 mA Z*: 110 Ω @ 2000 MHz	Z@100 MHz: 300 Ω DCR: 0.06 Ω I _H : 3000 mA Z*: 330 Ω @ 110 MHz	Z@100 MHz: 600 Ω DCR: 0.10 Ω I _H : 2000 mA Z*: 700 Ω @ 90 MHz	Z@100 MHz: 1000 Ω DCR: 0.30 Ω I _H : 1000 mA Z*: 1100 Ω @ 90 MHz	
1806	742 792 30 ■	742 792 3 ■	742 792 310 ■	742 792 311 ■	742 792 312 ■	
	Z@100 MHz: 32 Ω DCR: 0.30 Ω I _H : 400 mA Z*: 70 Ω @ 1000 MHz	Z@100 MHz: 90 Ω DCR: 0.30 Ω I _H : 400 mA Z*: 180 Ω @ 1000 MHz	Z@100 MHz: 30 Ω DCR: 0.05 Ω I _H : 3000 mA Z*: 50 Ω @ 900 MHz	Z@100 MHz: 52 Ω DCR: 0.05 Ω I _H : 3000 mA Z*: 90 Ω @ 1000 MHz	Z@100 MHz: 65 Ω DCR: 0.03 Ω I _H : 3000 mA Z*: 110 Ω @ 1000 MHz	
1812	742 792 4 ■	742 792 42 ■	742 792 410 ■	742 792 411 ■	742 792 45 ■	742 792 44 ■
	Z@100 MHz: 60 Ω DCR: 0.30 Ω I _H : 400 mA Z*: 130 Ω @ 1000 MHz	Z@100 MHz: 150 Ω DCR: 0.50 Ω I _H : 200 mA Z*: 280 Ω @ 500 MHz	Z@100 MHz: 60 Ω DCR: 0.01 Ω I _H : 6000 mA Z*: 120 Ω @ 1000MHz	Z@100 MHz: 80 Ω DCR: 0.04 Ω I _H : 3000 mA Z*: 140 Ω @ 1000 MHz	Z@100 MHz: 110 Ω DCR: 0.035 Ω I _H : 4000 mA Z*: 170 Ω @ 600 MHz	Z@100 MHz: 850 Ω DCR: 0.10 Ω I _H : 1500 mA Z*: 1250 Ω @ 50 MHz
	742 792 5 ■	742 792 50 ■	742 792 510 ■	742 792 511 ■	742 792 515 ■	742 792 52 ■
	Z@100 MHz: 120 Ω DCR: 0.30 Ω I _H : 300 mA Z*: 200 Ω @ 800 MHz	Z@100 MHz: 70 Ω DCR: 0.30 Ω I _H : 300 mA Z*: 180 Ω @ 1000 MHz	Z@100 MHz: 70 Ω DCR: 0.03 Ω I _H : 6000 mA Z*: 120 Ω @ 1000 MHz	Z@100 MHz: 120 Ω DCR: 0.05 Ω I _H : 3000 mA Z*: 190 Ω @ 600 MHz	Z@100 MHz: 785 Ω DCR: 0.05 Ω I _H : 3000 mA Z*: 1300 Ω @ 60 MHz	Z@100 MHz: 880 Ω DCR: 0.035 Ω I _H : 4000 mA Z*: 940 Ω @ 1200 MHz
	742 793 0	742 793 1	742 793 2	742 752 1	742 751 1	742 751 2
	Size: 4.0 x 3.0 x 2.55 Z@100 MHz: 42 Ω DCR: 0.006 Ω I _H : 6000 mA	Size: 8.5 x 3.0 x 2.55 Z@100 MHz: 91 Ω DCR: 0.009 Ω I _H : 6000 mA	Size: 7.8 x 4.75 x 3.0 Z@100 MHz: 98 Ω DCR: 0.009 Ω I _H : 6000 mA	Size: 9.0 x 5.6 x 2.5 Z@100 MHz: 52 Ω DCR: 0.01 Ω I _H : 5000 mA	Size: 8.0 x 5.0 x 4.6 Z@100 MHz: 416 Ω DCR: 0.01 Ω I _H : 5000 mA	Size: 11.0 x 4.65 x 5.0 Z@100 MHz: 580 Ω DCR: 0.003 Ω I _H : 5000 mA

*max.

- High Speed
- Wide Band
- High Current

All products
ex stock!

Please check datasheets on www.we-online.com for specifications.
Würth Elektronik eiSos GmbH & Co. KG, EMC & Inductive Solutions © 2010

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[Wurth Elektronik:](#)

[742791](#)